



LBB 1957/00 Plena Voice Alarm Keypad

- ▶ Seven zone selection keys
- ▶ LED indications for zone selection
- ▶ Up to eight keypads can be connected together

The keypad is an extension to the LBB 1956/00 Plena Voice Alarm Call Station that adds seven additional zone-select keys. It has the same stable metal base as the call station. In addition to tabletop use, the special design allows it to be neatly flush-mounted in desktops.

Functions

Each call station supports six zone selections. Connecting one of these units, adds seven zones or zone groups that can be selected. Up to eight keypads can be added to an LBB 1956/00 call station. LEDs on the keypad indicate the active zones.

Controls and indicators

- Seven zone selection keys
- Seven zone selection LEDs
- Eight DIP switches

Interconnections

- Two RJ45 jacks
- 24 VDC input
- Keypad connector

Certifications and Approvals

Safety	acc. to EN 60065
Immunity	acc. to EN 55103-2
Emission	acc. to EN 55103-1

Technical Specifications

Electrical

Power Supply

Voltage range	24 VDC supplied by LBB 1956/00
Current consumption	<15 mA

Mechanical

Base dimensions	40 x 100 x 235 mm (1.57 x 3.97 x 9.25 in)
Weight	Approx. 1 kg
Mounting	Bracket coupled with LBB 1956/00 or other LBB 1957/00
Color	Charcoal with silver

Environmental

Operating temperature	-10 °C to +55 °C (14 °F to +131 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

Ordering Information

LBB 1957/00 Plena Voice Alarm Keypad