



# LBB 4432/00 Call Station Keypad



- ▶ Eight freely programmable selection keys
- ▶ Serial data and power interface to call station basic
- ▶ Up to 16 keypads can be connected to one call station basic
- ▶ Activation indicator for each key
- ▶ Stylish and modern design

The call station keypad is used in combination with the call station basic to make manual or pre-recorded announcements to any assigned zones, to select the zones or to execute pre-defined actions. The call station keypad has eight programmable buttons, each with a two-color status LED.

## Functions

The keys of the call station keypad can be programmed for actions, such as:

- Controlling functions: selection recall, call activation, cancel selection, BGM off, BGM volume control, fault acknowledgement, etc.
- Selecting sources: BGM channel, pre-recorded messages, attention and alarm tones
- Selecting destinations: zones and zone groups

The keys can be programmed for different modes of operation, such as momentary or toggle. Each key has one two-color status LED beside it. Beside each LED is a transparent, removable tab that can hold a function or zone label for the key. Safety covers to prevent accidental activation of the keys are available as an option.

The keypad gets its power from the call station it is connected to.

## Controls and indicators

- Eight function keys

- Eight two-color LEDs

## Interconnections

- Two serial data and power connections

## Certifications and Approvals

Region	Certification	
Europe	CE	Declaration of Conformity
	TUEV-SUED	TUV
	GL	GL
Safety	acc. to IEC 60065-98	
Immunity	acc. to EN 55103-2	
Emissions	acc. to EN 55103-1 / FCC-47 part 15B	
EVAC (TÜV certified)	acc. to IEC 60849 / BS 5839-8	

## Parts Included

Quantity	Component
1	LBB 4432/00 Call Station Keypad
1	Flat cable
1	Coupling bracket
1	Set of text labels

## Technical Specifications

### Electrical

Power consumption 1.1 W (DC)

### Mechanical

Dimensions (H x W x D) 70 x 95 x 200 mm (2.8 x 3.7 x 7.9 in)

Weight 0.3 kg (0.7 lb)

Mounting Bracket attachment to a call station or other keypad

Color Charcoal

### Environmental

Operating temperature -5 °C to +55 °C (+23 °F to +131 °F)

Storage temperature -20 °C to +70 °C (-4 °F to +158 °F)

Humidity 15% to 90%

Air pressure 600 to 1100 hPa

## Ordering Information

**LBB 4432/00 Call Station Keypad** **LBB4432/00**  
has eight programmable buttons, each with a two-color status LED.

### Accessories

**LBB 4436/00 Set of Key Covers (10 pcs)** **LBB4436/00**  
10 key covers and 10 replacement lenses

**Americas:**  
Bosch Security Systems, Inc.  
Communications Systems  
12000 Portland Avenue, South  
Burnsville, Minnesota 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@US.bosch.com  
www.boschcommunications.us

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: +31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2600  
Fax: +65 6571 2698  
apr.securitysystems@bosch.com  
www.boschsecurity.com

**Represented by**