

**BOSCH**

Invented for life

# LBC 1256/00 EVAC Connection Adapter



The LBC 1256/00 is an EVAC connection adapter, to be installed in series with the 100 V primary connection of a loudspeaker unit, changing the loudspeaker into a BS 5839-8 compliant unit. This additional connection adapter ensures that, in the event of a fire, damage to the loudspeaker does not result in failure of the circuit to which it is connected. In this way, system integrity is maintained. The connection adapter consists of a 3-pole ceramic screw terminal block with a pre-mounted thermal fuse. It can replace a connection terminal or be mounted in a standard connection box. The LBC 1256/00 consists of 100 pieces.

## Ordering Information

**LBC 1256/00 EVAC Connection Adapter**  
3-pole screw connector, 100 pieces

**LBC1256/00**

## Technical Specifications

### Mechanical

Approx. dimensions	19 x 37 x 22 mm (0.75 x 1.46 x 0.87 in)
Type	3-pole screw connector
Material	Ceramic
Thermal fuse	150 °C
Pack contents	100 pieces
Weight	40 g (1.4 oz)

**Americas:**

Bosch Security Systems, Inc.  
Communications Systems  
12000 Portland Avenue, South  
Burnsville, Minnesota 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@US.bosch.com  
www.boschcommunications.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6258 5511  
Fax: +65 6319 3499  
apr.securitysystems@bosch.com  
www.boschsecurity.com

**Represented by**